



Deckenaufbauleuchte LED Surface-mounted LED downlight

8 321 0.5 050

8 321 0.6 050

Schutzart - Protection IP 65

Schutzklasse - Safety Class I



MONTAGE ANLEITUNG Mounting instructions



WILLY MEYER & SOHN GMBH & CO.KG

LICHTTECHNISCHE SPEZIALFABRIK

Stemmessiepener Weg 5 • D-58675 Hemer

Deckenaufbauleuchte LED
mit 25 Watt Hochleistungs-LED Modul

MONTAGEHINWEISE

Anschluß der Leuchte nach VDE 0100.

Deckenaufbauleuchte für ungeschützte Anlagen.

Vor dem Öffnen der Leuchte Netzspannung trennen !

Oberen Gewindestift an der Leuchte lösen und Montagedose durch Linksdrehung entnehmen.

Montagedose mit beiliegendem

Befestigungsmaterial anbringen.

Dichtscheiben unter den Schrauben !

Schrauben mit 2,5 Nm anziehen.


Auf richtigen Sitz der elektrischen Zuleitung in den Dichtungen achten !

Beim Aufsetzen der Leuchte auf die Wanddose elektrische Verbindung durch Stecker herstellen.

Leuchtengehäuse auf die Montagedose setzen und durch Linksdrehung bis zum Anschlag verriegeln.

Gewindestift fest anziehen.


Das Glas ist ein Einscheiben-Sicherheits-Hartglas.



Die Leuchte darf nur mit ihren vollständigen Schutzabdeckungen betrieben werden.

Leuchte	Gewicht	Windangriffsfläche
8 321 ...	2,0 kg	0,03 m ²

In Strahlrichtung den Mindestabstand zu angestrahlten Flächen einhalten !



Surface-mounted LED downlight
with 25 Watts high performance LED module

MOUNTING INSTRUCTIONS

Connection of light fitting in compliance with the prevailing regulations in your country.

Luminaire for non-protected, outdoor installation.

Disconnect luminaire from power supply before opening.

Loosen upper grub screw on the side of the luminaire and remove the mounting box by turning to the left.

Attach mounting box to the ceiling using the fixing materials provided.

Important: Use sealing washers under the screws !


Tighten screws with 2.5 Nm.

Ensure that the power supply cable sits correctly in the cable entry grommet.

When placing luminaire over mounting box, make electrical connection using the plug connector.

Place luminaire over mounting box and turn it as far as possible to the left.

Tighten grub screw. The glass is tempered safety glass.



Luminaire may be operated only when all protective covers are in place.

Luminaire	Weight	Projected area
8 321 ...	2.0 kg	0.03 m ²

Ensure that the minimum spacing between luminaire and illuminated surface is observed.

